## How to download the firmware to the GW-7553 module?

Step 1: Download the newest firmware (7553vxx.exe & autoexec.bat) at

ftp://ftp.icpdas.com.tw/pub/cd/fieldbus\_cd/profibus/gateway/gw-7553/firmware/

Step 2: Open the cover of GW-7553

Step 3: Close the initial pin 2, 3 (JP1) and flash protection pin 1, 2 (JP2) by jumper



Step 4: Connect the power supply







Step 6: Turn the power on

Step 7: Run MiniOS7 utility in the PC (You can download MiniOS7 Utility at <a href="http://ftp.icpdas.com.tw/pub/cd/8000cd/napdos/minios7/utility/minios7\_utility/">http://ftp.icpdas.com.tw/pub/cd/8000cd/napdos/minios7/utility/</a> )

Step 8: Connect MiniOS7 Utility and the GW-7553 by click the connection button.



Step 9: Erase 7553vxx.exe & autoexec.bat

😹 Minio57 Utility Verion 3.2.1								
🔯 File 🕨 Connection + 🐟 Commant 😰 Configuration 🛅 Tools 🛷 Help +								
Look jn: 🛅 V11	🔽 🔇 🤣 📂		Lock in: Disk A	✓ 376,329 bytes av	ailable	e <sup>rte</sup>		
Name 7 186wu iai 7 185wu iai 7552v11.52E autoewee bat	Size Type 90K8 應用程式 1K6 總用程式 00K8 應用程式 1K8 MS-DOS 赴次檔案	Modified 2009/4/18 T + 01-19 2009/1/30 L + 09 2009/106 T + 02-52 2009/6/11 T + 03.02	No Name	Run Run with parameters Rest MiniS F4 Enwe Dick	Size 82.316 11	Modfied 2008/6/11 174-03:52:00 2008/6/11 174-03:52:29		
			i7186EX>COM1, 2 files(s) 82,3	127 bytes				
🕨 Connection(F2) 🗐 Upload(F	5) 💐 DiskTool(F6) 🛅 Info(F7)	🔯 Delete(F8) 🛃 Refres	n(F9) 📇 Console(F10) 📼	DOS(F11) 🚧 Search(F12)				

Step	10: Select the new firmware	(7553vxx.exe)	and autoexec.bat and upload
------	-----------------------------	---------------	-----------------------------

🚵 MiniOS7 Utility Ferion 3.2.1								
🕼 File 🆕 Connection 👻 🐟 Command 😰 Configuration 🛅 Tools 🥔 Help 🔹								
Look in: 🛅 V13	💌 G 🌶 🖻			Lock in: Disk A	A 💌	458,720 bytes available	ł	
Name	Size Type	Modified	No	Name		Size	Modified	
7188xw.exe	90KB 應用程式	2008/4/18下午 01:19						
7188xw.ini	1KB 組態設定値	2009/11/30 上午 09:						
7552v13.exe	80KB 應用程式	2009/7/10 上午 07:53						
autoexec.bat	<u>U</u> pload	F5 9///10 <u>F</u> + 0/:53						
	Upload & Execute[RAM]							
	Up <u>d</u> ate MiniOS7 Image							
	DOS	F11						
<		>						
			i7186EX:	COM1, 0 files(s	s) O bytes			
🕞 Connection(F2) 🗊 Upload(F5) 📚	DiskTool(F6)	🔞 Delete(F8) 🛃 Refresh(I	9) 🚝	Console(F10)	🔤 DOS(F11)	🔹 Search(F12)		

Step 11: Complete download the firmware

Mini/087 Hillity Verion 3.2.1											
Commentant Commentant - tools - reth -											
Look jn: 🛅 firmware		3 🕸 🖻				Lock in: Disk A		~	256,393 bytes available	e	đ
Name	Size	Туре	Modified	$\square$	No	Name		I.	S	bize	Modified
🚾 7188xw.exe	90KB	應用程式	2008/4/18下午 01:19		<b>  </b> 0	7553v12.exe			202,2	252	2009/9/10 上午 09:00:00
💌 7188xw.ini	1KB	組態設定値	2009/11/30 上午 09:		<b>   </b> 1	autoexec.bal	t			11	2009/9/10 上午 09:00:00
7553v12.exe	197KB	應用程式	2009/9/10上午 09:00								
💽 autoexec.bat	1KB	MS-DOS 批次檔案	2009/9/10 上午 09:00	Н							
<			>								
				i	7186E×	>COM1, 2 files(s	) 202,263 bytes				
					o) (#=	C	Dec(511)	A	A. C		
Connection(F2) Upload(F	oj 🦉 Disk Fi		Uelete(F8) 🔂 Hefresi	n(F	J) 🔁	Console(FIU)		6	g Search(F12)		

## Step 12: Turn the power off

Step 13: Close the initial pin 2, 3 (JP1) and flash protection pin 1, 2 (JP2) by jumper



Step 14: Close the cover of GW-7553