

Classification	System and Application FAQ on WinCE PAC				No.	2-006-00	
Author	Eric_Shiu	Version	1.0.0	Date	2018/04/27	Page	1/3

## How to recover the default factory settings

*Applies to:*

<i>Platform</i>	<i>OS Version</i>	<i>PAC Utility Version</i>
<i>WinPAC</i>	<i>All Versions</i>	<i>All Versions</i>
<i>ViewPAC</i>	<i>All Versions</i>	<i>All Versions</i>

### Tips & Warnings



The following settings are affected in the recovery operation. Before recovering the default factory settings, record the current settings if necessary.

*Default factory settings:*

*System Settings->Display resolution: 800\*600(WP-8x2x/WP-9000/WP523x)*

*System Settings->Display resolution: 800\*480(VP-2201)*

*System Settings->Display resolution: 640\*480(VP-1231)*

*System Settings->Display resolution: 800\*600(VP-4231/VP-4201)*

*System Settings->Display resolution: 1024\*768(VP-6231/VP-6201)*

*Ethernet Settings->LAN1 (LAN2): DHCP enabled*

*FTP Settings->Access->Allow Anonymous: Enabled*

*FTP Settings->Access->Allow Anonymous Upload: Enabled*

*Auto Execution: empty*

***Multi-serial port wizard: uninstalled***

***Touch Panel Drivers: uninstalled***

*Control Panel->Power->Schemes->Switch state to User Idle: Never*

*Control Panel->Power->Schemes->Switch state to System Idle: Never*


*Control Panel->Network and Dial-up Connections: The settings of LAN1/2*

You can recover the default factory settings as you need or an unexpected problem occurs with the following steps:


Classification	System and Application FAQ on WinCE PAC				No.	2-006-00	
Author	Eric_Shiu	Version	1.0.0	Date	2018/04/27	Page	2/3

## Step1. Reboot in Safe mode


1.1. Turn the rotary switch on the device to “1”, and then boot up the WinPAC/ViewPAC



1.2. After rebooting, Click the “OK” button.




1.3. Turn the rotary switch to “0”.



Classification	System and Application FAQ on WinCE PAC				No.	2-006-00	
Author	Eric_Shiu	Version	1.0.0	Date	2018/04/27	Page	3/3

## Step2. Recover the default factory settings

2.1. Start the WinPAC/ViewPAC Utility, and click “**File**” → “**Save and Reboot**” on the menu.



2.2. Click the “**Yes**” button and wait for the device to reboot.

