本文件提供 InduSoft PAC 本體安裝/專案下載之使用參考

1. 在 InduSoft 資料夾中,開啟"CEServer.exe"

| dit | View | <u>G</u> 0 | Favorites | | | | | | | |
|-------------------|-----------|------------|-----------|--------------------------|-------------------------------|--------------------|---------------|----------|----------|----------|
| s Wi | cro_SD\Ir | nduSo | ft | | MARAERICERCOLOGICA | | | | | |
| | B | • | | - | - | - | - | | R | R |
| 28888 | Drv | | WebAddOn | MyRapi | MyRapiGe | OPCComn | StudioSnmp | StudioSn | CEServer | WibuCm |
| 1 | | | | | | | | | | |
| J Ver | | | | R | lemote Agent | t (¥8.1) | × | | | |
| | | | | | Connection status | : remote client | | | | |
| | | | | | Log: | remote chorn | | | | |
| | | | | | Runtime was start | ted. | - | | | |
| | | | | | | | - | | | |
| | | | | | Device connection (TCP/IP) | via Network | Start | | | |
| | | | | | | Setup | E <u>x</u> it | | | |
| | | | | | IP(s): 192.168.0. | 10 | | | | |
| | | | | | | | | | | |
| | | | | | | | | | | |
| | | | | | | | | | ~ | |
| | | | | | | | | | 43 | |
| and the second is | | Sec. State | | The states of the states | | | | | | |

2. 此時會跳出是否啟用安全性系統的提示,可依需求做選擇。若選擇 Yes 則會進入 Security System 啟用設定頁。

| Edit | View | Go | Favorites | | | | | | |
|---------|-----------|--------|------------------------------------|---|---|---|---|---------------------------------|------------------------|
| dress W | licro_SDV | InduSe | oft | | | | | | MCM |
| > | P | 7 | Ø | - | - | - | | | |
| Bin | Drv | , | WebAddOn | MyRapi | MyRapiGe | . OPCComn | . StudioSnmp | StudioSn | CEServer W |
| | | | | | | | | | |
| Server | | | | R | emote Agen | t (v8.1) | × | | |
| | | | | P | onnection statu | s: | Market States | | |
| | | | | P | lot connected to | o remote client | | | The second second |
| | | Ren | note Agent | (v8.1) | | | | | × |
| | | 4 | You do n host from before yo | iot have sec n unauthoriz ou proceed. | urity enabled. ed access. It is Do you want | You need to a s strongly reco to configure se | enable security mmended that ecurity now? | in order to pr you configure | otect your seculity |
| | | | | | <u>Y</u> e | is <u>N</u> o | | | |
| | | | | I | P(s): 192.168.0. | 10 | | | |
| | | | | | | | | | |
| | | | | | | | AND STREET | | |
| | | | | | | | | | |
| | | | | | | | | | |
| | | | | | | | | | |

| Edit <u>V</u> iew | <u>G</u> o F <u>a</u> vorites | | |
|-------------------|-------------------------------|--|----------|
| ress Micro_SD\In | duSoft | | |
| 3 0 | | | |
| in Drv | WebAddon MyRa | api MyRapiGe OPCComn StudioSnmp StudioSn | CEServer |
| | | | |
| erver | | Remote Agent (v8.1) | |
| | | Connection status: | |
| | Domotor | Not connected to remote client | |
| | Remote A | | |
| | | you want to suppress this message on the next startup? | |
| | | Yes No | |
| | | IP(s): 192.168.0.10 | |
| | | | |
| | | | |
| | | | |
| | | R. | |
| | | | |

3. 若步驟 2 選擇 No, 系統則會詢問下次是否跳過步驟 2 的提示

4. 步驟 3 後,若當資料夾內已有專案,則會自動 Run 起專案,請切換視窗至 Remote Agent 框;若資料夾內尚未有專案則會提示 Incomplete 錯誤,請直接按 OK 回 Remote Agent 框,然後記下 Remote Agent 左下的 IP 位址

| dit <u>V</u> iew <u>G</u> o F <u>a</u> vorites | |
|--|---|
| s Micro_SD\InduSoft | |
| Drv WebAddOn MyRac | MyRapiGe OPCComp StudioSomo StudioSo (EServer With Co |
| 1 | |
| , rer | Remote Agent (v8.1) |
| | Connection status: Not connected to remote client |
| | Log: Runtime was started. |
| | Device connection via Network Start |
| | Setup Exit |
| | |
| | |
| | ß |

5. 回到 PC 的開發畫面,點擊 Connect 後跳出 Remote Management 對話框

| | InduSoft Web Studio |
|--|---|
| Home View Insert Project | Help |
| A Cut Copy Paste of Find/Replace Clipboard | Pownload Pownl |
| Project Explorer 🌐 📮 | Remote Management |
| Project: CustomWidget_test.APP Screens Main Screen Group Thin Clients Project Symbols Graphics Script Symbols Layout | Target Specify and connect to the target host before you can download your project and the run-time Project Import Embedded Lice Target Station O Host: 192.188.0.10 Serial Port: Advanced Microsoft ActiveSync Install system files Install system files Only newer files |

6. 在 Target 頁填入 IP 位址,並點擊 Connect 鈕與 PAC 連線

| Remote Managem | nent 📃 🗾 |
|--|---|
| Target Project Import Embedded Lice | Specify and connect to the target host before you can download your project and the run-time Target Station Host: 192.168.0.10 Serial Port: Advanced Microsoft ActiveSync Install system files Only newer files |
| | OK Cancel |

執行此步驟時可先備分 PAC 上的 InduSoft 資料夾。 在這個步驟中,您 PC 上的 InduSoft 版本將會覆蓋您的 PAC InduSoft 本體資料夾。 請注意您購買的 PAC 授權是否可適用於您在 PC 版上使用的版本。

把 Only newer files 框上的勾取消後, 點擊 Install system files....鈕, InduSoft 將會安裝至連線中的 PAC 上。

| Remote Managem | ient 🗾 |
|--|--|
| Target Project Import Embedded Lice | Specify and connect to the target host before you can download your project and the run-time Target Station Host: 192.168.0.10 Serial Port: Advanced Microsoft ActiveSync Install system files Only newer files |
| | OK Cancel |

8. 在 Project 頁上把 Only newer files 框上的勾取消,然後點擊 Download...鈕,您在 PC 上的專案將會下載至 PAC 上

| ſ | Remote Managem | nent 🗾 🗾 |
|---|----------------|---|
| | Target | Download your project to the target device |
| l | Project | |
| | Import | Project Path Local: BaymondWDocumentsWinduSoft Web Studio v8.1 ProjectsWCustomWidget_testW |
| | Embedded Lice | Target: \Micro_SD\InduSoft\Custom\Idget_test\} |
| | | Download Only newer files Run Status: |
| | | Send File Stop |
| | | |
| | | |
| | | |
| | | OK Cancel |

7.