分類	在 WinCE PAC	系統和應用時常見問	題		編號	2-022-00
作者	Eric_Shiu	版本 1.0.0	日期	2018/04/27	頁碼	1/4
	如	回設定File(SMB)	server		
庭田圦						
應而穴	· 平台	OS 版本	-	PAC u	Itility 版本	
	WinPAC	所有版本		所	有版本	
	VIEWPAC	所有版本	<u> </u>	所	有版本	
請依照-	下列步驟操作,設定File	server				
步 驟1:	執行桌面的PAC utility->	"Network Setting"	->File serv	ver settings •		
步 驟2:	按"Setting"鍵後,將會路	兆出設定視窗。				
File H	ity [1.2.2.1] lelp		步驟1			
General	Display IP Config Netwo	rk Device Information	n Auto Exec	ution Rotary Exe	cution M	→
Access	Login File Server Cettings		1		<u> </u>	
Your	on create a petworked file e	arver and enables cliq	oto to otoro :	and		
retrie	eve files, and makes use of th	erver and enables clienter internet for commu		inu /een		
	t devices and other shared ed	quipment.	沙 廠 2			
	Settings	>				
	Ι	CP DAS Co., Ltd. 7	Technical d	ocument		

分類	在 WinCE PAC	系統和應	目時常見問題			編號	2-022-00
作者	Eric_Shiu	版本	1.0.0	日期	2018/04/27	頁碼	2/4

步驟 3: 輸入裝置名稱,如果沒有指定,將使用預設值。

注意:同網域有兩台以上的WinPAC,請個別設定不同的裝置名稱,否則另外一台的File server將無法正堂運作。

Share Files System Setting ▼ Device Name (Each device need setting a different device name) ▼ WP9000 The path to the folder to be shared Temp Configure the file server to use LANx as the network adapter LANI ▼ Device Name (Each device need setting a cressible to all users on the network adapter LANI ▼ Device Name (Each device need setting a different device name) Ptop (Each device need setting a different device name) WP9000 Device Name (Each device need setting a different device name) WP9000 Device Name (Each device need setting a different device name) WP9000 Device Name (Each device need setting a different device name) WP9000 The path to the folder to be shared Nump Configure the file server to use LANx as the network adapter LANI ▼ Enable all authentrication on the file server .	/ALL市建H ×	
a different device name) WP9000 The path to the folder to be shared Verap CANI Verap CANI Verap Vera	Share Files System Settings 📃 🗙 Device Name (Each device need setting	
The path to the folder to be shared Verup Configure the file server to use LANk as the network adapter LANI Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Jest 1 file 26pt pag #xpc, 0 File 3 File 4: file 26pt pag #xpc, 0 Law Share Files System Settings VP9000 The path to the folder to be shared VP9000 The path to the folder to be shared VP9000 The path to the folder to be shared VP9000 The path to the folder to be shared VP9000 Enable all authentication on the file server will not be accessible to all users on the network adapter LAN1 Enable all authentication on the file server will not be accessible to all users on the user to be allowed access to the file server	a different device name) Wegono	
Temp UANI WP9000 The path to the folder to be shared WP9000 The path to the folder to be shared WP9000 The path to the folder to be shared Temp Configure the file server to use LANk as the network adapter LANI Set Cancel OK Cancel OK Cancel OK	The path to the folder to be chared	
Configure the file server to use LANx as LANI LANI accessible to all users on the file server network and the "admin" as the user to be allowed access to the file server Set Help 步驟 4: 指定分享資料夾。 上意: 指定資料夾的名稱,最好不要夾雜空格,例: "Program file"。 Share Files System Settings evice Name (Each device need setting a different device name) WP9000 The path to the folder to be shared \Temp \Temp Configure the file server to use LANx as the network adapter LANI Configure the file server to use LANx as the network adapter LANI Set System_Disk Micro_SD Vertice Set Output Cancel Ok		
tenetwork adapter LANI LANI LANI Enable all authentication on the file server: The file server will not be accessible to all users on the file server Set Heip F K Configure the file server to use LANx as the network adapter LANI Configure the file server will not be server. The file server will not be ser	Configure the file server to use LANx as	
LLAN1 LAN1 LaN1 LaN1 LaN1 LaN1 Land Lan	the network adapter	
■ Bable all authentication on the file accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Help	LAN1	
Set 世史 伊藤 4: 指定分享資料夾。 注意: 指定資料夾的名稱,最好不要夾雜空格,例: "Program file"。 Share Files System Settings _ × Device Name (Each device need setting a different device name) WP9000 The path to the folder to be shared \Temp Configure the file server to use LANx as the network adapter LAN1 Enable all authentication on the file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Cancel Ok	 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server 	
Help 步驟 4: 指定分享資料夾。 注意: 指定資料夾的名稱,最好不要夾雜空格,例: "Program file"。 Share Files System Settings × Device Name (Each device need setting a different device name) × WP9000 vice Information The path to the folder to be shared vice Information (Temp Configure the file server to use LANx as the network adapter Buwse for Folder LAN1 ✓ Enable all authentication on the file server will not be accessible to all users on the network adapter to be allowed access to the file server Network Set Cancel Ok	Set	
步驟 4: 指定分享資料夾。 注意: 指定資料夾的名稱,最好不要夾雜空格,例: "Program file"。 Share Files System SettingsX Device Name (Each device need setting a different device name) WP9000 The path to the folder to be shared \Temp Configure the file server to use LANx as the network adapter LAN1 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set	нер 📉	
Share Files System Settings Device Name (Each device need setting a different device name) WP9000 The path to the folder to be shared \Verture \Verture \Verture Configure the file server to use LANx as the network adapter LAN1 Image: Lange all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Cancel Ok	步驟 4: 指定分享資料夾。 注章:指定資料來的名稱,最好不要	[[] 來雜空格,例:"Program file"。
Device Name (Each device need setting a different device name) WP9000 The path to the folder to be shared \Temp \Temp Configure the file server to use LANx as the network adapter LAN1 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set		
a different device name) WP9000 The path to the folder to be shared \Temp Configure the file server to use LANx as the network adapter LAN1 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set	Device Name (Each device need setting	
WP9000 The path to the folder to be shared \Temp \Temp Configure the file server to use LANx as the network adapter LAN1 Enable all authentication on the file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Cancel Ok	a different device name)	
WP9000 The path to the folder to be shared \Temp Configure the file server to use LANx as the network adapter LAN1 ✓ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server My Device Set Cancel Ok	·	evice Information Auto Execution Rotary Exe
The path to the folder to be shared \Temp Configure the file server to use LANx as the network adapter My Device LAN1 ▼ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Network Set Cancel Ok	WP9000	
\Temp Browse for Folder Configure the file server to use LANx as the network adapter My Device LAN1 ✓ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Natwork Set Cancel Ok	The path to the folder to be shared	
Configure the file server to use LANx as the network adapter My DLvice LAN1 ▼ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Network Set Cancel Ok	\Temp	Bruwse for Folder
the network adapter LAN1 ▼ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Network Set Cancel Ok	Configure the file server to use LANx as	My Device
LAN1 ✓ Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server ✓ Set Cancel	the network adapter	Network
 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server Set Cancel 	LAN1	System_Dist
Set Cancel Ok	 Enable all authentication on the file server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server 	Wilcro_SD USB_Disk Recycled Temp Windows
	Set	Cancol
Help	Help	

ICP DAS Co., Ltd. Technical document

分類	在 WinCE PA	在 WinCE PAC 系統和應用時常見問題					
作者	Eric_Shiu	版本	1.0.0	日期	2018/04/27	頁碼	3/4
步驟 5: 選擇 連線, 否則只 注意:File ser Share Files S Device Name (a different dev WP9000 The path to the \Temp Configure the f the network ad LAN1 LAN1 LAN1 LAN2 Server. accessib network user to b file serve	要由哪組 LAN 作為 有 Admin 的帳號 ver 使用的帳號與 stem Settings Each device need se- ice name) e folder to be shared ile server to use LAN apter	A與 File S 可以與 Fil FTP 使用 Ting	Server 連線, e Server 連線 的帳號相同	並選擇是	否允許所有使	用者都可」	以與 File serv
	Set						

步驟 6: 按下"Setting",完成設定

Share Files System Settings 🛛 🔄 🗙	
Device Name (Each device need setting a different device name)	
WP9000	evice Inforr
The path to the folder to be shared	
	and enable rnet for co
	ОК
The password of the ID 'admin' is the same	as FTP.
server. The file server will not be accessible to all users on the network and the "admin" as the user to be allowed access to the file server	
Cot	

Help

ICP DAS Co., Ltd. Technical document

分類	在 WinCE PA	C系統和應	應用時常見問	題		編號	2-022-00
作者	Eric_Shiu	版本	1.0.0	日期	2018/04/27	頁碼	4/4
步驟 7: 在網址3 號與與密碼(EX: 注意:如果使用"\\ WP8X4X01 (W) 檔案E 編輯E) ()上一頁 ▼ () 網址()	刘輸入 WinPA ID Admin, PV \ LAN1 IP"無〉 P8x4x01) 檢視☑ 我的₽ ● - ♪ ♪	C 的"\\ LA V Admin) 去跟 WinP 愛愛(ム) エ!) 搜尋 <i>[</i> 〕	AN1 IP"或是 ,開始 PC AC 連線, 【① 說明(出) 資料夾 111	≝" <u>\\裝置名稱</u> 與 File(SM 可以改使用	≝"(例:WP8x4 B) server 連緣]"\\裝置名稱"	x01) ,連 泉。 。	線後,輸入帳
網路 工作 其他位置	(3	名稱 ② Mic	ro_SD				
詳細資料 ₩P8X4X01 (₩	(7 (78x4x01)						
				Cochnical do	cument		